





Small Signal Schottky Diode



Features

Moisture sensitivity level 1

Reverse voltage: 40V/30V/20VAverage forward current: 350mA

Application

High frequency and low voltage rectifier

Mechanical data

• Package: SOD-323

• Terminals: Tin plated leads, solderable per

J-STD-002 and JESD22-B102

■ Maximum Ratings (Ta=25°C Unless otherwise specified)

| Parameter | Symbol | Unit | Value | |
|--|------------------|------|-------------|----|
| | | | SD103AWS | S4 |
| Device marking code | | | SD103BWS | S5 |
| | | | SD103CWS | S6 |
| Forward current | l _F | mA | 350 | |
| Non-repetitive surge peak forward current @ t=8.3ms half-sine wave | | 1.5 | | .5 |
| Non-repetitive surge peak forward current @ t=1ms square wave | I _{FSM} | A | 5 | |
| Power dissipation | P_{D} | mW | 200 | |
| Junction temperature | T_J | ℃ | -55 to +125 | |
| Storage temperature | T_{STG} | ℃ | -55 to +150 | |





■ Electrical Characteristics (T_a=25°C Unless otherwise specified)

| Parameter | Symbol | Unit | Conditions | | Min | Тур | Max |
|-------------------------|----------------|------|----------------------------|-----------------------|-----|-----|------|
| Reverse voltage | | | SD103AWS | | 40 | | |
| | V_R | V | SD103BWS | I _R =100uA | 30 | | |
| | | | SD103CWS | | 20 | | |
| Forward voltage | V_{F1} | ٧ | I _F =20 | mA | | | 0.37 |
| Forward voltage | V_{F2} | V | I _F =200 | OmA | | | 0.60 |
| | | | SD103AWS | V _R =30V | | | 5 |
| Reverse leakage current | I _R | uA | SD103BWS | V _R =20V | | | 5 |
| | | | SD103CWS | V _R =10V | | | 5 |
| Junction capacitance | Cj | pF | V _R =0V, f=1MHZ | | | | 50 |

■ Thermal Characteristics

| Parameter | Symbol | Unit | Value |
|---|----------------------|------|-------|
| Thermal resistance, junction-to-ambient | RθJ-A ⁽¹⁾ | °C/W | 500 |
| Thermal resistance, junction-to-case | R0J-C ⁽¹⁾ | °C/W | 400 |

Note:

(1) Thermal resistance from junction to ambient and from junction to case mounted on P.C.B. with 8mm*9mm copper pad areas





■Characteristics




Fig 2: Capacitance Capability

Ta=25°C

Ta=25°C

Reverse Voltage V_R(V)

Fig 3: Typical Forward Characteristics





Fig 4: Typical Reverse Characteristics








■Ordering Information


| Preferred P/N | Packing code | Unit weight(g) | Minimum package(pcs) | Inner box quantity(pcs) | Outer carton quantity(pcs) | Delivery mode |
|------------------------|--------------|--------------------|-------------------------|----------------------------|----------------------------|---------------|
| SD103AWS THRU SD103CWS | F2 | Approximate 0.0048 | 3000 | 30000 | 120000 | 7" reel |
| SD103AWS THRU SD103CWS | F3 | Approximate 0.0048 | 10000 | 1 | 210000 | 13" reel |

■ Outline Dimensions



| DIMENSIONS | | | | | | |
|------------|--------|--------|--------|----------|--|--|
| DIM | INC | HES | ММ | | | |
| | MIN | MAX | MN | MAX | | |
| А | | 0.0393 | | 1.0000 | | |
| A1 | 0.0000 | 0.0039 | 0.0000 | 0.1000 | | |
| A2 | 0.0314 | 0.0354 | 0.8000 | 0.9000 | | |
| lo | 0.0098 | 0.0157 | 0.2500 | 0.4000 | | |
| С | 0.0031 | 0.0059 | 0.0800 | 0.1500 | | |
| D | 0.0472 | 0.0551 | 1,2000 | 1.4000 | | |
| Ε | 0.0629 | 0.0709 | 1,6000 | 1,8000 | | |
| E1 | 0.0984 | 0.1063 | 2.5000 | 2.7000 | | |
| L | 0.018 | 7TYP | 0.47 | 0.475TYP | | |
| L1 | 0.0098 | 0.0157 | 0.250 | 0.400 | | |
| ө | 0* | 8* | 0* | 8* | | |

■ Suggested Pad Layout







Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function, or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website http://www.21yangjie.com, or consult your nearest Yangjie's sales office for further assistance.